

Digital Thermometer WT-2

Technical parameters:

- ◆ Temperature measuring range: $-50^{\circ}\text{C} \sim +300^{\circ}\text{C}$ ($-58^{\circ}\text{F} \sim +572^{\circ}\text{F}$)
- ◆ Resolution: 0.1°C
- ◆ Accuracy: $\pm 1^{\circ}\text{C}$ ($0^{\circ}\text{C} \sim 60^{\circ}\text{C}$), $\pm 5^{\circ}\text{C}$ (other range)
- ◆ Power supply: DC1.5V, 7# Alkaline battery

Features:

- ◆ Switch between $^{\circ}\text{C}$ and $^{\circ}\text{F}$
- ◆ Data holding
- ◆ Max. Min. temperature memory
- ◆ Max. Min. temperature setting and alarm

Key description:

- ◆ ON/Off: Turn on/off the thermometer
- ◆ HOLD: Hold the measuring data
- ◆ SET: Alarming setting
- ◆ ADJ: Adjust the setting value
- ◆ AC: Cancel alarm
- ◆ MAX/MIN: Display Max. or Min. temperature
- ◆ OK: Save

Operation instructions:

- ◆ [ON/OFF]: Press to turn on the thermometer then enter into the measuring mode.
- ◆ [SET]: Press to enter into alarm setting mode.
- ◆ [ADJ] and [OK]: Press "SET" to enter into alarm setting mode. Alarming high temperature "HI" flashes. Press [ADJ] to add 1°C and add it faster when pressing the key for more than 2 sec. The temperature returns to be 1°C higher than the alarming low temperature when exceeds 300°C . Press OK to save and enter into alarming low temperature setting. "LO" flashes. Adjust it as the same way. "AL" displays in alarming mode. Alarm sound lasts for 5 sec. and can be cancelled by press "AC".
- ◆ [AC]: Cancel alarm and enter into temperature measuring mode. "AL" disappears.